

Wiring Between Relay Set Strips

Call	g	L3 Common	to	TP24
RC	y	K1 Common	to	RA21
RGB	bn	RA22	to	RGB23
ST	g	L1 Cmmmon	to	D1/D2
STA	w/b	RA2	to	TP6
OPA	w	K2 Common	to	RR6
OPB	s	K3 Common	to	RR22
TA	w/b	L2 Common	to	T1(12)
RING	o/w	RT1	to	terminal behind resistors
US RST	w/o	RA4	to	RUS8
TPR	o	SC2	to	TP28
BB	s	R6(500ohms)	to	TP8

Wiring from Relay Sets to Strip Connection

B	bk	TP7	to	SC B
TO	b/r	TP1	to	SC TO
NUT	r/b	TP3	to	SC NUT
IRT	r/s	RUS6	to	SC irt
R	bk	RR2	to	SC R
OS	r/o	A3	to	SC OS
SPB	w/g	R3(450ohms)	to	SC SPB
SC	g/w	PHA1	to	SC SC
LP	o	BCO21	to	SC LP
BCO2	o	BCO2	to	SC BCO2
BL	o/y	SB3	to	SC BL
BS	y/o	SB1	to	SC BS
SA	w	C1	to	SC SA
SB	g	C2	to	SC SB

Wiring from Line Circuits to Strip Connection

	-	+	L	SK	SKA
1	g/y	y/g	o/w	bn/y	w/o
2	g/bk	bk/g	g/y	bk/b	y/g
3	bn/y	y/bn	w/bn	s/y	y/s
4	b/r	r/b	s/bk	g/r	r/g
5	o/w	w/o	s/r	w	r/s
6	b/bk	bk/b	r/s	bn/bk	bk/bn
7	g/bk	bk/g	bn/r	s/w	w/s
8	b/y	y/b	y/s	bn/w	w/bn
9	g/y	y/g	s/y	bn/y	y/bn

Rack Wiring between Relay Sets and Strip Connection

