


U6 is connected to the H (or P) wire of the local final selector. If any final has an earth on its H wire, then that earth will release relay H, as will any "dis" spare outlet. H1 will drive the unselector on to a free final selector. On a free final the 250 battery will be extended through the final N and B contacts to operate relay H. H1 then cuts the drive. We finish with the unselector standing on the first free outlet it finds and with the 250 ohm battery being extended to the group selector mult to mark the final as free.

| Parkend<br>Final Selector Traffic Distributor |            |   |
|---|------------|---|
| DFR ex019b                                    |            |   |
|   |            |   |
|   |            |   |
|   |            |   |
|   |            |   |
| ISSUE B                                       | 20/01/2018 | Operating note added  |
| ISSUE A                                       | 16/03/2006 | Opening Issue   |
| Dean Forest Railway                           |            |  |